



Straight Connector PT-JIC 37° Flare Male



Brass Mark : CPC
Soft Steel Mark : GPF
Stainless Steel Mark : CCC

Item No	Description	Thread		Dimension (mm)				
		T (PT)	T1 (UNF)	L	L1	L2	L3	H
I12	1/8 X 1/4	1/8-28	7/16-20	30				12
I13	1/8 X 5/16	1/8-28	1/2-20	31				14
I14	1/8 X 3/8	1/8-28	9/16-18	32				14
I22	1/4 X 1/4	1/4-19	7/16-20	34				14
I23	1/4 X 5/16	1/4-19	1/2-20	34				14
I24	1/4 X 3/8	1/4-19	9/16-18	35				14
I25	1/4 X 1/2	1/4-19	3/4-16	38.5				21
I42	3/8 X 1/4	3/8-19	7/16-20	36				17
I43	3/8 X 5/16	3/8-19	1/2-20	36				17
I44	3/8 X 3/8	3/8-19	9/16-18	37				17
I45	3/8 X 1/2	3/8-19	3/4-16	40.5				21
I46	3/8 X 5/8	3/8-19	7/8-14	40.5				23
I47	3/8 X 3/4	3/8-19	1 1/16-12	46				27
I52	1/2 X 1/4	1/2-14	7/16-20	40.5				21
I54	1/2 X 3/8	1/2-14	9/16-18	41.5				21
I55	1/2 X 1/2	1/2-14	3/4-16	43.5				21
I56	1/2 X 5/8	1/2-14	7/8-14	43.5				23
I57	1/2 X 3/4	1/2-14	1 1/16-12	49				27
I58	1/2 X 1	1/2-14	1 5/16-12	52				33.3
I74	3/4 X 3/8	3/4-14	9/16-18	44				27
I75	3/4 X 1/2	3/4-14	3/4-16	46				27
I76	3/4 X 5/8	3/4-14	7/8-14	48				27
I77	3/4 X 3/4	3/4-14	1 1/16-12	51				27
I78	3/4 X 1	3/4-14	1 5/16-12	54				33.3

Straight Connector PT-JIC 37° Flare Male



Brass Mark : CPC
Soft Steel Mark : GPF
Stainless Steel Mark : CCC

Item No	Description	Thread		Dimension (mm)				
		T (PT)	T1 (UNF)	L	L1	L2	L3	H
I85	1 X 1/2	1-11	3/4-16	50				33.3
I86	1 X 5/8	1-11	7/8-14	52				33.3
I87	1 X 3/4	1-11	1 1/16-12	55				33.3
I88	1 X 1	1-11	1 5/16-12	56				33.3
I89	1 X 1 1/4	1-11	1 5/8-12	59				41
I8A	1 X 1 1/2	1-11	1 7/8-12	64				50
I97	1 1/4 X 3/4	1 1/4-11	1 1/16-12	58				41
I98	1 1/4 X 1	1 1/4-11	1 5/16-12	59				41
I99	1 1/4 X 1 1/4	1 1/4-11	1 5/8-12	61				41
I9A	1 1/4 X 1 1/2	1 1/4-11	1 7/8-12	67				50
I9D	1 1/4 X 2	1 1/4-11	2 1/2-12	76				65
IA8	1 1/2 X 1	1 1/12-11	1 5/16-12	62				50
IA9	1 1/2 X 1 1/4	1 1/12-11	1 5/8-12	64				50
IAA	1 1/2 X 1 1/2	1 1/12-11	1 7/8-12	67				50
IAD	1 1/2 X 2	1 1/12-11	2 1/2-12	76				65
ID9	2 X 1 1/4	2-11	1 5/8-12	72				65
IDA	2 X 1 1/2	2-11	1 7/8-12	75				65
IDD	2 X 2	2-11	2 1/2-12	81				65